

RF Wireless Remote Control Radio Controller / Transmitter & Receiver

Package Include:

- 1 x Receiver: S1XM-DC06 / S1XM-DC09 / S1XM-DC12 / S1XM-DC24 (1 Channel / Momentary Control Mode)
- 2 x Transmitter: C-1
- 1 x User manual

Feature:

Wireless control, easy to install
Direct power output; control Lights, Motors, Fans, electrically operated Doors/Locks/Windows/Blinds/Cars or Other Appliances.
You can turn on/off the receiver with transmitter (remote control) from any place within a reliable distance; the wireless RF signal can pass through walls, floors and doors.
With characteristics of reverse power protection and over current protection
Audible / visual indication
Use microcontroller model of EM78P156, an 8-bit microprocessor designed and developed with low-power and high-speed CMOS technology.
Reliable control: The transmitter (Encoding) and the receiver (Decoding) use an 8-bit code.
One/several transmitters can control one/several receivers simultaneously.
If you use two or more receivers in the same place, you can set them with different codes.
Transmitting Frequency: 315MHz / 433MHz

Receiver:

Model No.: S1XM-DC06 / S1XM-DC09 / S1XM-DC12 / S1XM-DC24

Channel: 1 CH

Control Mode: Momentary (Press and hold -> On; Release -> Off)

Coding Type: Fixed code

Coding Setting: By soldering

Power Supply (Operating Voltage): DC6V (S1XM-DC06), DC12V±1V (S1XM-DC12), DC9V±1V (S1XM-DC09), DC24V±1V (S1XM-DC24)

Output: DC6V (S1XM-DC06), DC12V (S1XM-DC12), DC9V (S1XM-DC09), DC24V (S1XM-DC24)

PCB Size: 70mm x 48mm x 21mm

Case Size: 75mm x 55mm x 28mm

Maximum Working Current: 10A

Transmitter:

Model No.: C-1

Channel: 1 CH

Remote Control Distance: 100m / 300ft (theoretically)

Encode: Fixed code by soldering

Unit size: 58mm x 39mm x 16mm

Power Supply: 1 x 23A -12V battery (included, can be used for 12 months)

Usage:

Press and hold button: Turn on the relay, terminal A&B output DC power.

Release the button: Turn off the relay, terminal A&B no output.

