

## AC 110V or 220V or 380V Contactor Motor Starter Relay 3-Phase Pole 32A

### Feature:

ABS flame retardant plastics

AC contactor (aka motor starter) is a high capacity relay. It is often used to control a motor or as a main power switch.

It's used for long range connection and circuit disconnection, frequent activation and controlling AC motor.

### Specification:

Model No.: 0040011

Three main contact: All Normally Open

One auxiliary contact: Normally Open

Contact: Silver

Max. Current: 32A

Contact Rating: 220V/32A/7.5KW, 380V/32A/15KW, 690V/32A/18.5KW

Control (Coil) Voltage: 110VAC, or 220VAC, or 380VAC (You must specify the coil voltage. Otherwise, 220V coil will be sent out as default choice)

Weight: 570g

Dimensions: 57mm x 86mm x 100mm

Mounting Method: 35mm DIN Rail or Screw On.