

37mm 12V 295RPM Heavy Duty High Torque Gear Box DC Motor

Feature:

Gearhead motor
High quality
With metal cover
Built-in cooling fan
Heavy duty design
Runs in either direction by reversing power supply polarity
Benefiting from high torque and low noise, this motor is solidly constructed and ready to install in numerous applications

Specifications:

Diameter: 37mm
Length (excluding shaft): 92.5mm
Total length: 119mm
Shaft length: 15.5mm
Shaft diameter: 6mm
Front panel 3.0mm Screw for fixing this motor
Nominal voltage: 12V DC
Operating voltage range: 3 - 18V DC
No load speed at 12 V: 295 rpm
No load current: 1.6A
Load speed: 250 rpm
Load current: 2A
Operating torque: 12kg.cm
Stall torque: 80kg.cm
Stall current: 7A
Gear ratio: 1:56
Power: 60W
Weight: 300g

Application:

Mainly used for remote-controlled car, electric motorbike, ATV, Kart, robot, rolling blind and electric projector, etc.

Warning:

Owing to large torque and high power, the starting current of motor is relatively large, up to 6A. After starting the motor, the current will be back to normal, about 1A~2A. You should choose high power supply above 10A, or else you cannot start the motor.

