

## 37mm 24V 22RPM Heavy Duty High Torque Gear Box DC Motor

### Feature:

Gearhead motor  
High quality  
With metal cover  
Built-in cooling fan  
Heavy duty design  
Runs in either direction by reversing power supply polarity  
Benefiting from high torque and low noise, this motor is solidly constructed and ready to install in numerous applications

### Specifications:

Diameter: 37mm  
Length (excluding shaft): 49.2mm  
Total length: 74.2mm  
Shaft length: 15.5mm  
Shaft diameter: 6mm  
Front panel 3.0mm Screw for fixing this motor  
Nominal voltage: 24V DC  
Operating voltage range: 12 - 30V DC  
No load speed at 24 V: 22rpm  
No load current: 30A  
Load speed: 18rpm  
Load current: 50A  
Operating torque: 5kg.cm  
Stall torque: 20kg.cm  
Stall current: 0.8A  
Gear ratio: 270  
Power: 0.7W  
Weight: 170g

### Application:

Mainly used for remote-controlled car, electric motorbike, ATV, Kart, robot, rolling blind and electric projector, etc.

### Warning:

Do not frequently stall the motor, or else the gear of motor will be broken.  
Owing to large torque and high power, the starting current of motor is relatively large, up to 6A. After starting the motor, the current will be back to normal, about 1A~2A. You should choose high power supply above 10A, or else you cannot start the motor.

