## High Torque AC 220V Permanent Magnet SynchronousMotor 60MM

## Application:

Mainly used for monitor platform, electric equipment, automatic instrument, electric advertising banner, screen machine, pouch laminator, mahjong table, cash register, vending machine, electronic ticket machineand all small power and low constant speed equipment.

#### Feature:

High torque and low noise Low power consumption Small size, light w eight Easy to use Gearhead motor High quality All-metal gear No speed regulation

Rotate forward & reverse, direction can be changed by changing wiring

# ${\bf Specifications:}$

Diameter: 60mm

Length (excluding shaft): 61mm

Total length: 85mm Shaft length: 22mm Shaft diameter: 7mm

Front panel 4.5mm Screw for fixing this motor Working voltage range: 220V~240V AC

Working current: 60mA Working power: 14W

Weight: 550g	
working power: 14w	

Rated speed (RPM)	2.5	5	10	15	20	30	40	50	60	80	100
Output torque (N.CM)	350	250	150	100	75	50	37.5	30	25	20	15

### Wiring:

Two yellow wires on the motor are connected to terminal "N". Red wire or blue wire is connected to terminal "L".

If red wire is connected to terminal "L", the motor rotates in forward direction.

If blue wire is connected to terminal "L", the motor rotates in reverse direction.

